




MVP3 MAIN BOARD QUICK GUIDE

HL-188(MVP3)Quick Guide



1.	DIMM x 2 Sockets	15.	Power LED&Key Lock
2.	AT K/B Connector	16.	J14: HDD LED
3.	PS/2 Mouse Connector		J15: ATX Switch On/ Orr
4.	ATX Power Connector		J16: RESET
5.	AT Power Connector		J17: TB LED J18: TB S/W
6.	FDD Connector	17.	IDE Connector
7.	LPT Connector	18.	J11:AT 1-2, ATX 2-3
8.	AGP Slot	19.	CPU Voltage Setting
9.	COM1, COM2 Connector	20.	ZIF Sockets 7
10.	PCI x 3 Slots	21.	SIMM x 2 Sockets
11.	IrDA Connector	22.	DRAM Voltage
12.	BIOS Voltage		J6-J7: 1-25.0V 2-3 3.3V
13.	ISA x 3 Slots	23.	CPU Clock
14.	Spk Connector	24.	CPU Bus Clock

SI CPU Bus Clock Jumper Setting

		S1(1)	S1(2)	S1(3)	S1(4)	S1(5)	S1(6)	S2
INTEL 200 MHZ	66*3.0		SHORT			SHORT	SHORT	SH(2)
INTEL 233 MHZ	66*3.5					SHORT	SHORT	SH(2)
AMD K6 233 MHZ	66*3.5					SHORT	SHORT	SH(2)
AMD K6 266 MHZ	66*4.0	SHORT		SHORT		SHORT	SHORT	SH(2)
AMD K6 300 MHZ	66*4.5	SHORT	SHORT	SHORT		SHORT	SHORT	SH(2)
AMD K6 333 MHZ	66*5.0		SHORT	SHORT		SHORT	SHORT	SH(2)
AMD K6-2 350 MHZ	100*3.5							SH(1,3)
AMD K6-2 400 MHZ	100*4.0	SHORT		SHORT				SH(1,3)
AMD K6-2 450 MHZ	100*4.5	SHORT	SHORT	SHORT				SH(1,3)
CyrixMII 300 MHZ	66*3.5					SHORT	SHORT	SH(2)
CyrixMII 300 MHZ	75*3.0		SHORT				SHORT	SH(1,2)
CyrixMII 333 MHZ	83*3.0		SHORT			SHORT		SH(1)

SI CPU CLOCK

	1.5X	2.0X	2.5X	3.0X	3.5X	4.0X	4.50X	5.0X	5.5X
1		SHORT	SHORT			SHORT	SHORT		
2			SHORT	SHORT			SHORT	SHORT	
3						SHORT	SHORT	SHORT	SHORT

CMOS Clear Function Select

JUMPER	Normal	Clear
J12	1-2	2-3

AT & ATX Power Setting

JUMPER	AT	ATX
J11	1-2	2-3

SW1 CPU Voltage setting

	1	2	3	4
2.0V				
2.1V	SHORT			
2.2V		SHORT		
2.3V	SHORT	SHORT		
2.4V			SHORT	
2.5V	SHORT		SHORT	
2.6V		SHORT	SHORT	
2.7V	SHORT	SHORT	SHORT	
2.8V				SHORT
2.9V	SHORT			SHORT
3.0V		SHORT		SHORT
3.1V	SHORT	SHORT		SHORT
3.2V			SHORT	SHORT
3.3V	SHORT		SHORT	
3.4V		SHORT	SHORT	SHORT
3.5V	SHORT	SHORT	SHORT	SHORT

S2 CPU BUS CLOCK

1	2	3	4	CLOCK
	SHORT			66
SHORT	SHORT			75
SHORT				83
SHORT		SHORT		100